

Light-O-Rama



ShowTime Eight Channel Deluxe Lighting Controller

LOR800Wg3 DMX

www.lightorama.com

- Weather resistant NEMA 3R enclosure
- 8 independent high-power channels
- 15 amp capacity (about 4500 mini-lights)
- "Ghost loads" to prevent LED glow and smooth out LED fading
- Effects include on, off, fade, intensity, twinkle and shimmer
- Storage for an internal lighting control sequence that can be run standalone
- Can direct itself and a network of controllers
- Can be directed by the MP3 Director, another controller or by the ShowTime Windows Software
- Can monitor inputs to start a sequence
- Up to 240 controllers (3,840 channels) in a network
- 100 intensity levels for dimming
- 256 levels for smooth fading with durations from 0.1 to 25 seconds
- Settable high burn (to extend lamp life) and low burn (to reduce lamp shock)



Front cover removed

The LOR800Wg3 is a microprocessor based lighting controller. It takes commands from an internal stored sequence, another controller, a Light-O-Rama MP3 Director, the Light-O-Rama ShowTime Windows PC software or any DMX lighting control software/software.

The microprocessor performs the lighting effects from high level commands, for example: fade channel 12 from 20% intensity to 60% intensity over six seconds. This internal intelligence allows for very complex shows where thousands of changes in the lights are possible every second.

Using the MP3 Director or the ShowTime Windows PC software, the display can be choreographed to music.

A network of controllers allows animation of displays requiring high power and/or hundreds or even thousands of channels.

Easy to use software with powerful wizards facilitates the building of sophisticated lighting sequences choreographed to music and the assembly of the sequences into shows. The only limit is your imagination.

Specifications	
Configuration	8 channels
Channel Capacity	8 amps
Controller Capacity	15 amps
Supply Voltage	120 VAC 50/60 Hz
Isolation	Opto isolate line voltage from control logic
Power Connections	Input(s) NEMA 5-15P Outputs NEMA 5-15R
Control In/Out	RS485 via RJ45 or RJ11
Dimensions (case)	8" w x 10" h x 5" d

Light-O-Rama, Inc.
Tel: (518) 539-9000 Fax: (518) 538-0067
info@lightorama.com